



Tuner Box S2

colour options:  

Micro-sized FM-Tuner
MSRP 169 €
(incl. VAT)

- Micro-sized FM-Tuner
- 99 presets
- Manual or automatic tuning
- Adaptive noise reduction
- High-contrast dot-matrix display
- Display of frequency, preset number, centre of station, Stereo or Mono reception, signal strength
- Trigger switching (on/off)
- Full function IR remote control
- Aluminium case in new S2 design
- Available in silver or black

Tuning range FM-band:	87,5 - 108MHz (50kHz steps)
Programmable presets:	99
Frequency response:	20Hz - 20kHz (± 1 dB)
S/N ratio:	50dB
THD:	0,05% / Δf 75kHz and f mod 1kHz
Stereo separation:	30dB / Δf 75kHz and f mod 1kHz
Sensitivity:	7dB / μ V mono, 17dB / μ V stereo / 75 ohms
Antenna input:	1 x co-axial DIN-socket (75 ohms) / US-model F-socket
Line-level output:	1 pair RCA/phono sockets
Trigger in and out:	2-pole coaxial 2,5mm jack
Output voltage:	0,775Vrms
Outboard power supply:	5V/1A DC; 110-240V/50, 60Hz
Power consumption:	70mA DC, <1W in standby
Dimensions W x H x D:	103 x 37 x 112 (121) mm
Weight:	315g without power supply

Tuner Box S2 - A lot of radio in a compact box

This small FM-only tuner is fully loaded with high-quality audio and useful features. 99 station presets are more than enough to store your favourite radio stations. Tuner Box S2 can ideally be used in combination with other Box design components. For example, the Trigger In and Out allow you to remotely power on and off the Tuner Box S2 via a Pre Box S2 Analogue. The included full functional IR-remote and the high-contrast dot-matrix display make this unit a delight to use!

