

Pre Box S2 Analogue

Stereo Line preamplifier

- Advanced circuitry with premium components
- Neutral sound with superior low noise floor
- 3 Stereo Line inputs
- 1 Fixed line level output
- 1 Pre output
- Motorised volume control
- SMD for short signal paths
- Low output impedance for low loss with long cables
- Gold-plated connections
- Remote control for on/off, input select, volume
- Trigger outputs for Amp Box and Switch Box
- Alu/Metal casing protects against vibration and interference
- Available in black and silver

Technical data

Frequency response	20Hz - 80kHz
Noise floor	-105dB (A weighted)
THD+N	0,0005%
Gain	8,5dB
Pre out	1 x RCA
Fixed output	1 x 3.5mm
Output voltage typically	1V at 1kHz
Line-level inputs	2 x RCA, 1 x 3.5mm
Input impedance	15kohms
Trigger out	2-pole 2,5mm co-axial jack
Outboard power supply	5V/500mA DC, suitable for your country's mains supply
Standby power consumption	< 1 watt
Dimensions W x H x D	103 x 37 x 120 mm
Weight	405g (without power supply)



SRP
€ 269,00

Audiophile pre-amplifier with 3 line inputs and remote control!

Pre Box S2 Analogue features three line level inputs, two pairs of RCA sockets as well as a separate 3.5 millimeter input. Three individual analogue signals can be passed on to a power amplifier, such as Amp Box S2 or other Pro-Ject Box Design power amplifiers, via the RCA pre-output! A fixed line level signal can be relied to a further amplifier such as Head Box S2 via the 3.5mm output. A 12V trigger output can remotely turn on other products with trigger input for improved comfort and convenience. The incredibly low harmonic distortion levels guarantee a listening experience which has never been available in this pricerange! The housing is made of an aluminium/metal sandwich construction for highest aesthetics and to protect against unwanted electromagnetic interference and vibrations. Pre Box S2 Analogue comes in silver or black and can be powered by any 5V power-bank or the supplied power supply.

black version



rear view

- ◇ 2xRCA In
- ◇ 2x3.5mm
- ◇ 1xRCA Out
- ◇ Trigger out
- ◇ Power

